Hamlet

USB 2.0 TO LAN USB 2.0 to LAN Adapter 10/100Mbit



Driver Installation Guide for Mac

www.hamletcom.com

Caution

DO NOT connect the Ethernet Adapter to your computer before you install the provided driver.

Mac OS installation

- 1. Open "ASIX_USB_Device_Installer_macOS..." folder and double-click the **ASIX_USB_Device_Installer_v1.0.0.dmg** image file.
- 2. Double-click the **ASIX_USB_Device_Installer_v1.0.0.pkg** installation package to install the driver.

	ASIX_USB_Device_Installer	
🤹 🐳		
ASIX_USB_Device_Installer ASIX_USB_	Device_Uninistal	
_v1.0.0.pkg ler_v	/1.0.0.pkg	

3. In the window that appears, please click on **Continue** to start the installation wizard.

	Welcome to the AONY LIOP Device the teller leadeller	
	Welcome to the ASIX_USB_Device_Installer Installer	
Introduction	You will be guided through the steps necessary to install this software	
Read Me	software.	
Destination Select		
Installation Type		
Installation		
 Summary 		
	Go Back Continue	•

4. Click **Continue** to proceed.



5. When the following window appears, click **Install** to install the driver.

• • •	Install ASIX_USB_Device_Installer	
	Standard Install on "Untitled"	
 Introduction Read Me Destination Select Installation Type Installation Summary 	This will take 1,4 MB of space on your computer. Click Install to perform a standard installation of this software on the disk "Untitled".	
	Customise Go Back Install	

6. Type in the password of your system and press **Install Software** button.

Enter your pa	ssword to a	llow this.	
Username:	delme		
Password:	•••••		
		Cancel	Install Software

- 7. Wait for the installation to complete and restart the computer if required.
- 8. After system reboot, open Launchpad and click ASIX_USB_Device_App icon.



9. When ASIX USB Ethernet Controller window appears, connect the adapter to a USB port of your computer then press **Activate** button.

	ASIX USB Ethernet Controller
	Activate Deactivate
1.Please p 2.Click Ac 3.You may Press "Op 4.Unplug	vlug your device. tivate button. y get message "System Extension Blocked". pen Security Preferences" and click Allow button. your device then plug again.
* Uninsta	llation flow:
1.Click De	activate button.

10. If the System Extension Blocked window appears, press Open Security Preferences.



11. In **Security & Privacy**, click the lock icon at the bottom left of the pane to unlock the preference pane and allow app execution.

	General FileVault Firewall Privacy
AI	gin password has been set for this user Change Password
	Require password 5 minutes 📀 after sleep or screen saver begins
	Show a message when the screen is locked Set Lock Message
	✓ Disable automatic login
All	w apps downloaded from: App Store App Store and identified developers
All	w apps downloaded from: App Store App Store and identified developers rem software from application "ASIX_USB_Device_App" was

12. In the window that appears, type in Username and Password then press **Unlock**.



- 13. Now you can press Allow button in Security & Privacy pane.
- 14. Unplug and plug back in HNU2F100 adapter to complete installation.
- 15. Once installation is complete, HNU2F100 adapter will appear as **AX88772B** device in **Network** preference window like in the following picture.

Loca	tion: Automatic	0
AX88772B Connected Bluetooth PAN Not Connected	Status:	Connected AX88772B is currently active and has the IP address 10.1.3.41.
♥i-Fi ● Off	Configure IPv4:	Using DHCP
Thunderbolt Bridge	IP Address:	10.1.3.41
Not Connected	Subnet Mask:	255.255.0.0
	Router:	10.1.5.254
	DNS Server:	10.1.1.8, 10.1.1.9
	Search Domains:	careca.intranet
+ - 0.		Advanced ?
		Devert Area

Note: The screenshots shown in these steps depend on the version of your operating system and may vary slightly.